

# **OsmoGbProxy VTY Reference**

Copyright © 2019

This work is copyright by sysmocom - s.f.m.c. GmbH. All rights reserved.

**COLLABORATORS**

	<i>TITLE :</i> OsmoGbProxy VTY Reference		
<i>ACTION</i>	<i>NAME</i>	<i>DATE</i>	<i>SIGNATURE</i>
WRITTEN BY		October 22, 2020	

**REVISION HISTORY**

NUMBER	DATE	DESCRIPTION	NAME
v1	2nd December 2019	Initial	hw

# Contents

<b>1</b>	<b>VTY reference</b>	<b>1</b>
1.1	Common Commands . . . . .	1
1.1.1	end . . . . .	2
1.1.2	exit . . . . .	2
1.1.3	help . . . . .	2
1.1.4	list . . . . .	2
1.1.5	show running-config . . . . .	3
1.1.6	write . . . . .	3
1.1.7	write file [PATH] . . . . .	3
1.1.8	write memory . . . . .	3
1.1.9	write terminal . . . . .	4
1.2	view . . . . .	4
1.2.1	enable . . . . .	4
1.2.2	logging color (0 1) . . . . .	4
1.2.3	logging disable . . . . .	5
1.2.4	logging enable . . . . .	5
1.2.5	logging filter all (0 1) . . . . .	5
1.2.6	logging filter nsvc (nseilnsvci) <0-65535> . . . . .	6
1.2.7	logging level (lgprslnslbssgpllgloballlapdlinpllmuxllmilmibllsmsllctrlllgtpl... . . . . .	6
1.2.8	logging level force-all (debug info notice error fatal) . . . . .	8
1.2.9	logging level set-all (debug info notice error fatal) . . . . .	8
1.2.10	logging print category (0 1) . . . . .	9
1.2.11	logging print category-hex (0 1) . . . . .	10
1.2.12	logging print extended-timestamp (0 1) . . . . .	10
1.2.13	logging print file (0 1 basename) [last] . . . . .	11
1.2.14	logging print level (0 1) . . . . .	11
1.2.15	logging set-log-mask MASK . . . . .	12
1.2.16	logging timestamp (0 1) . . . . .	12
1.2.17	logp (lgprslnslbssgpllgloballlapdlinpllmuxllmilmibllsmsllctrlllgtplllstatsllgs... . . . . .	12
1.2.18	no logging level force-all . . . . .	14

1.2.19	show alarms . . . . .	15
1.2.20	show asciidoc counters . . . . .	15
1.2.21	show gbproxy [stats] . . . . .	15
1.2.22	show gbproxy links . . . . .	16
1.2.23	show history . . . . .	16
1.2.24	show logging vty . . . . .	16
1.2.25	show ns . . . . .	17
1.2.26	show ns (nseilnsvc) <0-65535> [stats] . . . . .	17
1.2.27	show ns persistent . . . . .	17
1.2.28	show ns stats . . . . .	18
1.2.29	show online-help . . . . .	18
1.2.30	show rate-counters . . . . .	18
1.2.31	show stats . . . . .	19
1.2.32	show stats level (global peer subscriber) . . . . .	19
1.2.33	show talloc-context (application all) (full brief DEPTH) . . . . .	19
1.2.34	show talloc-context (application all) (full brief DEPTH) filter REGEXP . . . . .	20
1.2.35	show talloc-context (application all) (full brief DEPTH) tree ADDRESS . . . . .	21
1.2.36	show version . . . . .	21
1.2.37	terminal length <0-512> . . . . .	22
1.2.38	terminal no length . . . . .	22
1.2.39	who . . . . .	22
1.3	enable . . . . .	22
1.3.1	configure terminal . . . . .	23
1.3.2	copy running-config startup-config . . . . .	23
1.3.3	delete-gbproxy-link <0-65534> (stale de-registered) . . . . .	23
1.3.4	delete-gbproxy-link <0-65534> (tllilimsilsgsn-nsei) IDENT . . . . .	24
1.3.5	delete-gbproxy-peer <0-65534> (only-bvc only-nsvc all) [dry-run] . . . . .	24
1.3.6	delete-gbproxy-peer <0-65534> bvc <2-65534> . . . . .	25
1.3.7	disable . . . . .	25
1.3.8	logging color (0 1) . . . . .	25
1.3.9	logging disable . . . . .	26
1.3.10	logging enable . . . . .	26
1.3.11	logging filter all (0 1) . . . . .	26
1.3.12	logging filter nsvc (nseilnsvc) <0-65535> . . . . .	27
1.3.13	logging level (lgprs nslbssgpl global lapdlinp mux millsms ctrl gtpl ...)	27
1.3.14	logging level force-all (debug info notice error fatal) . . . . .	29
1.3.15	logging level set-all (debug info notice error fatal) . . . . .	29
1.3.16	logging print category (0 1) . . . . .	30
1.3.17	logging print category-hex (0 1) . . . . .	31

1.3.18	logging print extended-timestamp (0 1) . . . . .	31
1.3.19	logging print file (0 1 basename) [last] . . . . .	32
1.3.20	logging print level (0 1) . . . . .	32
1.3.21	logging set-log-mask MASK . . . . .	33
1.3.22	logging timestamp (0 1) . . . . .	33
1.3.23	logp (lgprs ns bssgpl global lapd linp lmux mill mib lmsms ctrl gtpl stats lgs...) . . . . .	33
1.3.24	no logging level force-all . . . . .	35
1.3.25	nsvc (nseilnsvci) <0-65535> (block unblock reset) . . . . .	36
1.3.26	show alarms . . . . .	36
1.3.27	show asciidoc counters . . . . .	36
1.3.28	show gbproxy [stats] . . . . .	37
1.3.29	show gbproxy links . . . . .	37
1.3.30	show history . . . . .	37
1.3.31	show logging vty . . . . .	38
1.3.32	show ns . . . . .	38
1.3.33	show ns (nseilnsvc) <0-65535> [stats] . . . . .	38
1.3.34	show ns persistent . . . . .	39
1.3.35	show ns stats . . . . .	39
1.3.36	show online-help . . . . .	39
1.3.37	show rate-counters . . . . .	40
1.3.38	show startup-config . . . . .	40
1.3.39	show stats . . . . .	40
1.3.40	show stats level (global peer subscriber) . . . . .	41
1.3.41	show talloc-context (application all) (full brief DEPTH) . . . . .	41
1.3.42	show talloc-context (application all) (full brief DEPTH) filter REGEXP . . . . .	42
1.3.43	show talloc-context (application all) (full brief DEPTH) tree ADDRESS . . . . .	42
1.3.44	show version . . . . .	43
1.3.45	terminal length <0-512> . . . . .	43
1.3.46	terminal monitor . . . . .	44
1.3.47	terminal no length . . . . .	44
1.3.48	terminal no monitor . . . . .	44
1.3.49	who . . . . .	45
1.4	config . . . . .	45
1.4.1	banner motd default . . . . .	45
1.4.2	banner motd file [FILE] . . . . .	45
1.4.3	enable password (8!) WORD . . . . .	46
1.4.4	enable password LINE . . . . .	46
1.4.5	gbproxy . . . . .	46
1.4.6	hostname WORD . . . . .	47

1.4.7	line vty . . . . .	47
1.4.8	log alarms <2-32700> . . . . .	47
1.4.9	log file .FILENAME . . . . .	48
1.4.10	log gsmtap [HOSTNAME] . . . . .	48
1.4.11	log stderr . . . . .	48
1.4.12	log syslog (authpriv cron daemon ftplib prlmail news user uucp) . . . . .	49
1.4.13	log syslog local <0-7> . . . . .	49
1.4.14	no banner motd . . . . .	50
1.4.15	no enable password . . . . .	50
1.4.16	no hostname [HOSTNAME] . . . . .	50
1.4.17	no log alarms . . . . .	51
1.4.18	no log file .FILENAME . . . . .	51
1.4.19	no log stderr . . . . .	51
1.4.20	no log syslog . . . . .	52
1.4.21	no service advanced-vty . . . . .	52
1.4.22	no service terminal-length [<0-512>] . . . . .	52
1.4.23	no stats reporter log . . . . .	53
1.4.24	no stats reporter statsd . . . . .	53
1.4.25	ns . . . . .	53
1.4.26	password (8!) WORD . . . . .	54
1.4.27	password LINE . . . . .	54
1.4.28	service advanced-vty . . . . .	54
1.4.29	service terminal-length <0-512> . . . . .	55
1.4.30	show history . . . . .	55
1.4.31	stats interval <1-65535> . . . . .	55
1.4.32	stats reporter log . . . . .	56
1.4.33	stats reporter statsd . . . . .	56
1.5	config-log . . . . .	56
1.5.1	logging color (0 1) . . . . .	56
1.5.2	logging filter all (0 1) . . . . .	57
1.5.3	logging filter nsvc (nseilnsvci) <0-65535> . . . . .	57
1.5.4	logging level (lgprs nslbssgpl global lapd linp lmux lmmib lmsms lctr lgtp ...)	58
1.5.5	logging level force-all (debug info notice error fatal) . . . . .	60
1.5.6	logging level set-all (debug info notice error fatal) . . . . .	60
1.5.7	logging print category (0 1) . . . . .	61
1.5.8	logging print category-hex (0 1) . . . . .	61
1.5.9	logging print extended-timestamp (0 1) . . . . .	62
1.5.10	logging print file (0 1 basename) [last] . . . . .	62
1.5.11	logging print level (0 1) . . . . .	63

1.5.12	logging timestamp (0 1) . . . . .	63
1.5.13	no logging level force-all . . . . .	63
1.6	config-stats . . . . .	64
1.6.1	disable . . . . .	64
1.6.2	enable . . . . .	64
1.6.3	level (global peer subscriber) . . . . .	64
1.6.4	local-ip ADDR . . . . .	65
1.6.5	mtu <100-65535> . . . . .	65
1.6.6	no local-ip . . . . .	65
1.6.7	no mtu . . . . .	65
1.6.8	no prefix . . . . .	66
1.6.9	prefix PREFIX . . . . .	66
1.6.10	remote-ip ADDR . . . . .	66
1.6.11	remote-port <1-65535> . . . . .	66
1.7	config-line . . . . .	67
1.7.1	bind A.B.C.D [<0-65535>] . . . . .	67
1.7.2	login . . . . .	67
1.7.3	no login . . . . .	67
1.8	config-ns . . . . .	68
1.8.1	encapsulation framerelay-gre enabled (1 0) . . . . .	68
1.8.2	encapsulation framerelay-gre local-ip A.B.C.D . . . . .	68
1.8.3	encapsulation udp dscp <0-255> . . . . .	69
1.8.4	encapsulation udp local-ip A.B.C.D . . . . .	69
1.8.5	encapsulation udp local-port <0-65535> . . . . .	69
1.8.6	no nse <0-65535> . . . . .	70
1.8.7	nse <0-65535> encapsulation (udplframerelay-gre) . . . . .	70
1.8.8	nse <0-65535> fr-dlci <16-1007> . . . . .	71
1.8.9	nse <0-65535> nsvci <0-65534> . . . . .	71
1.8.10	nse <0-65535> remote-ip A.B.C.D . . . . .	71
1.8.11	nse <0-65535> remote-port <0-65535> . . . . .	72
1.8.12	nse <0-65535> remote-role (sgsnlbss) . . . . .	72
1.8.13	timer (tns-block tns-block-retries tns-reset tns-reset-retries tns-test tns-aliv... . . . . .	73
1.9	config-gbproxy . . . . .	73
1.9.1	acquire-imsi . . . . .	73
1.9.2	core-access-point-name (APN none) . . . . .	74
1.9.3	core-mobile-country-code <1-999> . . . . .	74
1.9.4	core-mobile-network-code <1-999> . . . . .	74
1.9.5	link stored-msgs-max-length <1-99999> . . . . .	75
1.9.6	link-list clean-stale-timer <1-999999> . . . . .	75

---

1.9.7	link-list keep-mode (never re-attach identified always)	75
1.9.8	link-list max-age <1-999999>	76
1.9.9	link-list max-length <1-99999>	76
1.9.10	match-imsi (patching routing) .REGEXP	77
1.9.11	no acquire-imsi	77
1.9.12	no core-access-point-name	77
1.9.13	no core-mobile-country-code	78
1.9.14	no core-mobile-network-code	78
1.9.15	no link stored-msgs-max-length	78
1.9.16	no link-list clean-stale-timer	79
1.9.17	no link-list max-age	79
1.9.18	no link-list max-length	79
1.9.19	no match-imsi	80
1.9.20	no patch-ptmsi	80
1.9.21	no secondary-sgsn	80
1.9.22	patch-ptmsi	80
1.9.23	secondary-sgsn nsei <0-65534>	81
1.9.24	sgsn nsei <0-65534>	81

# List of Tables

1.1	VTY Parameter Patterns	1
1.2	VTY port numbers	1

# Chapter 1

## VTY reference

The Virtual Tele Type (VTY) has the concept of nodes and commands. This chapter lists all nodes and the commands that are available within the node. Each command can consist out of several words followed by a variable number of parameters. There are common patterns for the parameters, these include IPv4 addresses, number ranges, a word, a line of text and choice. The following will explain the commonly used patterns.

Pattern	Example	Explanation
A.B.C.D	127.0.0.1	A IPv4 address
TEXT	example01	A single string without any spaces, tabs
.TEXT	Some information	A line of text
(OptionA OptionB OptionC)	OptionA	A choice between a list of available options
<0-10>	5	A number from a range

Table 1.1: VTY Parameter Patterns

The application is configured through the VTY. For configuring a system one needs to enter the **enable** node and then enter the **configure terminal** command. Then the configuration can be made according to the available commands. After the system has been configured one can use the **write** command to write the new configuration to the configuration file. The new file will be used after the application has been restarted.

The following table lists the TCP port numbers of the VTY for the various Osmocom GSM related programs as used on sysmocom products:

Port Number	Software
4240	osmo-pcu
4241	osmo-bts
4242	osmo-nitb, osmo-bsc
4243	osmo-bsc_mgcp
4244	osmo-bsc_nat
4245	osmo-sgsn
4246	osmo-gbproxy

Table 1.2: VTY port numbers

### 1.1 Common Commands

These commands are available on all VTY nodes. They are listed here only once, to unclutter the VTY reference.

### 1.1.1 end

Command

```
end
```

Parameters

end

End current mode and change to enable mode.

### 1.1.2 exit

Command

```
exit
```

Parameters

exit

Exit current mode and down to previous mode

### 1.1.3 help

Command

```
help
```

Parameters

help

Description of the interactive help system

### 1.1.4 list

Command

```
list
```

Parameters

list

Print command list

### 1.1.5 show running-config

Command

```
show running-config
```

Parameters

show

    Show running system information

running-config

    running configuration

### 1.1.6 write

Command

```
write
```

Parameters

write

    Write running configuration to memory, network, or terminal

### 1.1.7 write file [PATH]

Command

```
write file [PATH]
```

Parameters

write

    Write running configuration to memory, network, or terminal

file

    Write to configuration file

[PATH]

    Set file path to store the config, or replace if already exists

### 1.1.8 write memory

Command

```
write memory
```

Parameters

write

    Write running configuration to memory, network, or terminal

memory

    Write configuration to the file (same as write file)

### 1.1.9 write terminal

Command

```
write terminal
```

Parameters

write

Write running configuration to memory, network, or terminal

terminal

Write to terminal

## 1.2 view

The view node is the default node when connecting to the VTY interface. This node does not require any additional permission and allows to introspect the application.

### 1.2.1 enable

Command

```
enable
```

Parameters

enable

Turn on privileged mode command

### 1.2.2 logging color (0|1)

Command

```
logging color (0|1)
```

Parameters

logging

Configure logging

color

Configure color-printing for log messages

0

Don't use color for printing messages

1

Use color for printing messages

### 1.2.3 logging disable

Command

```
logging disable
```

Parameters

logging

Configure logging

disable

Disables logging to this vty

### 1.2.4 logging enable

This command is required to make logging commands available on the telnet VTY.

Command

```
logging enable
```

Parameters

logging

Configure logging

enable

Enables logging to this vty

### 1.2.5 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

Command

```
logging filter all (0|1)
```

Parameters

logging

Configure logging

filter

Filter log messages

all

Do you want to log all messages?

0

Only print messages matched by other filters

1

Bypass filter and print all messages

## 1.2.6 logging filter nservc (nsei|nsvci) <0-65535>

Command

```
logging filter nservc (nsei|nsvci) <0-65535>
```

Parameters

logging

Configure logging

filter

Filter log messages

nservc

Filter based on NS Virtual Connection

nsei

Identify NS-VC by NSEI

nsvci

Identify NS-VC by NSVCI

<0-65535>

Numeric identifier

## 1.2.7 logging level (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|l...

Command

```
logging level (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats| ↵
    lgsup|loap|lss7|lscap|lsua|lm3ua|lmgcp|ljibuf|lrspro) (debug|info|notice|error| ↵
    fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

gprs

GPRS Packet Service

ns

GPRS Network Service (NS)

bssgp

GPRS BSS Gateway Protocol (BSSGP)

lglobal

Library-internal global log family

llapd

LAPD in libosmogsm

linp

A-bis Input Subsystem

lmux

A-bis B-Subchannel TRAU Frame Multiplex

lmi

A-bis Input Driver for Signalling

lmib

A-bis Input Driver for B-Channels (voice)

lsms

Layer3 Short Message Service (SMS)

lctrl

Control Interface

lgtp

GPRS GTP library

lstats

Statistics messages and logging

lgsup

Generic Subscriber Update Protocol

loap

Osmocom Authentication Protocol

lss7

libosmo-sigtran Signalling System 7

lsccp

libosmo-sigtran SCCP Implementation

lsua

libosmo-sigtran SCCP User Adaptation

lm3ua

libosmo-sigtran MTP3 User Adaptation

lmgcp

libosmo-mgcp Media Gateway Control Protocol

ljbuf

libosmo-netif Jitter Buffer

lrsp

Remote SIM protocol

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.2.8 logging level force-all (debug|info|notice|error|fatal)

Command

```
logging level force-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.2.9 logging level set-all (debug|info|notice|error|fatal)

Command

```
logging level set-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

set-all

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.2.10 logging print category (0|1)

Command

```
logging print category (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem name

### 1.2.11 logging print category-hex (0|1)

Command

```
logging print category-hex (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')

### 1.2.12 logging print extended-timestamp (0|1)

Command

```
logging print extended-timestamp (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.2.13 logging print file (0|1|basename) [last]

Command

```
logging print file (0|1|basename) [last]
```

Parameters

logging

Configure logging

print

Log output settings

file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

basename

Prefix each log message with the source file's basename (strip leading paths) and line

[last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.2.14 logging print level (0|1)

Command

```
logging print level (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.2.15 logging set-log-mask MASK

Command

```
logging set-log-mask MASK
```

Parameters

logging

Configure logging

set-log-mask

Set the logmask of this logging target

MASK

List of logging categories to log, e.g. 'abc:mno:xyz'. Available log categories depend on the specific application, refer to the 'logging level' command. Optionally add individual log levels like 'abc,1:mno,3:xyz,5', where the level numbers are LOGL\_DEBUG=1 LOGL\_INFO=3 LOGL\_NOTICE=5 LOGL\_ERROR=7 LOGL\_FATAL=8

### 1.2.16 logging timestamp (0|1)

Command

```
logging timestamp (0|1)
```

Parameters

logging

Configure logging

timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp

### 1.2.17 logp (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgs...

Command

```
logp (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap ←  
      |lss7|lscpp|lsua|lm3ua|lmgcp|ljbuf|lrspro) (debug|info|notice|error|fatal) . ←  
LOGMESSAGE
```

Parameters

logp

Print a message on all log outputs; useful for placing markers in test logs

gprs  
GPRS Packet Service

ns  
GPRS Network Service (NS)

bssgp  
GPRS BSS Gateway Protocol (BSSGP)

lglobal  
Library-internal global log family

llapd  
LAPD in libosmogsm

linp  
A-bis Input Subsystem

lmux  
A-bis B-Subchannel TRAU Frame Multiplex

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp

libosmo-mgcp Media Gateway Control Protocol

ljbuf

libosmo-netif Jitter Buffer

lspro

Remote SIM protocol

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

.LOGMESSAGE

Arbitrary message to log on given category and log level

### 1.2.18 no logging level force-all

Command

```
no logging level force-all
```

Parameters

no

Negate a command or set its defaults

logging

Configure logging

level

Set the log level for a specified category

force-all

Release any globally forced log level set with 'logging level force-all <level>'

### 1.2.19 show alarms

Command

```
show alarms
```

Parameters

show

    Show running system information

alarms

    Show current logging configuration

### 1.2.20 show asciidoc counters

Command

```
show asciidoc counters
```

Parameters

show

    Show running system information

asciidoc

    Asciidoc generation

counters

    Generate table of all registered counters

### 1.2.21 show gbproxy [stats]

Command

```
show gbproxy [stats]
```

Parameters

show

    Show running system information

gbproxy

    Display information about the Gb proxy

[stats]

    Show statistics

### 1.2.22 show gbproxy links

Command

```
show gbproxy links
```

Parameters

show

    Show running system information

gbproxy

    Display information about the Gb proxy

links

    Show logical links

### 1.2.23 show history

Command

```
show history
```

Parameters

show

    Show running system information

history

    Display the session command history

### 1.2.24 show logging vty

Command

```
show logging vty
```

Parameters

show

    Show running system information

logging

    Show current logging configuration

vty

    Show current logging configuration for this vty

### 1.2.25 show ns

Command

```
show ns
```

Parameters

show

    Show running system information

ns

    Display information about the NS protocol

### 1.2.26 show ns (nsei|nsvc) <0-65535> [stats]

Command

```
show ns (nsei|nsvc) <0-65535> [stats]
```

Parameters

show

    Show running system information

ns

    Display information about the NS protocol

nsei

    Select one NSE by its NSE Identifier

nsvc

    Select one NSE by its NS-VC Identifier

<0-65535>

    The Identifier of selected type

[stats]

    Include Statistics

### 1.2.27 show ns persistent

Command

```
show ns persistent
```

Parameters

show

    Show running system information

ns

    Display information about the NS protocol

persistent

    Show only persistent NS

### 1.2.28 show ns stats

Command

```
show ns stats
```

Parameters

show

    Show running system information

ns

    Display information about the NS protocol

stats

    Include statistics

### 1.2.29 show online-help

Command

```
show online-help
```

Parameters

show

    Show running system information

online-help

    Online help

### 1.2.30 show rate-counters

Command

```
show rate-counters
```

Parameters

show

    Show running system information

rate-counters

    Show all rate counters

### 1.2.31 show stats

Command

```
show stats
```

Parameters

show

    Show running system information

stats

    Show statistical values

### 1.2.32 show stats level (global|peer|subscriber)

Command

```
show stats level (global|peer|subscriber)
```

Parameters

show

    Show running system information

stats

    Show statistical values

level

    Set the maximum group level

global

    Show global groups only

peer

    Show global and network peer related groups

subscriber

    Show global, peer, and subscriber groups

### 1.2.33 show talloc-context (application|all) (full|brief|DEPTH)

Command

```
show talloc-context (application|all) (full|brief|DEPTH)
```

Parameters

show

    Show running system information

talloc-context

    Show talloc memory hierarchy

application

    Application's context

all

    All contexts, if NULL-context tracking is enabled

full

    Display a full talloc memory hierarchy

brief

    Display a brief talloc memory hierarchy

DEPTH

    Specify required maximal depth value

### 1.2.34 show talloc-context (application|all) (full|brief|DEPTH) filter REGEXP

Command

```
show talloc-context (application|all) (full|brief|DEPTH) filter REGEXP
```

Parameters

show

    Show running system information

talloc-context

    Show talloc memory hierarchy

application

    Application's context

all

    All contexts, if NULL-context tracking is enabled

full

    Display a full talloc memory hierarchy

brief

    Display a brief talloc memory hierarchy

DEPTH

    Specify required maximal depth value

filter

    Filter chunks using regular expression

REGEXP

    Regular expression

### 1.2.35 show talloc-context (application|all) (full|brief|DEPTH) tree ADDRESS

Command

```
show talloc-context (application|all) (full|brief|DEPTH) tree ADDRESS
```

Parameters

show

    Show running system information

talloc-context

    Show talloc memory hierarchy

application

    Application's context

all

    All contexts, if NULL-context tracking is enabled

full

    Display a full talloc memory hierarchy

brief

    Display a brief talloc memory hierarchy

DEPTH

    Specify required maximal depth value

tree

    Display only a specific memory chunk

ADDRESS

    Chunk address (e.g. 0xdeadbeef)

### 1.2.36 show version

Command

```
show version
```

Parameters

show

    Show running system information

version

    Displays program version

### 1.2.37 terminal length <0-512>

Command

```
terminal length <0-512>
```

Parameters

terminal

    Set terminal line parameters

length

    Set number of lines on a screen

<0-512>

    Number of lines on screen (0 for no pausing)

### 1.2.38 terminal no length

Command

```
terminal no length
```

Parameters

terminal

    Set terminal line parameters

no

    Negate a command or set its defaults

length

    Set number of lines on a screen

### 1.2.39 who

Command

```
who
```

Parameters

who

    Display who is on vty

## 1.3 enable

The enable node is a privileged node, allowing to make changes to the configuration and to access further commands like 'configure'. All commands seen on the view node are also available here.

### 1.3.1 configure terminal

Command

```
configure terminal
```

Parameters

configure

    Configuration from vty interface

terminal

    Configuration terminal

### 1.3.2 copy running-config startup-config

Command

```
copy running-config startup-config
```

Parameters

copy

    Copy configuration

running-config

    Copy running config to...

startup-config

    Copy running config to startup config (same as write file)

### 1.3.3 delete-gbproxy-link <0-65534> (stale|de-registered)

Command

```
delete-gbproxy-link <0-65534> (stale|de-registered)
```

Parameters

delete-gbproxy-link

    Delete a GBProxy logical link entry by NSEI and identification

<0-65534>

    NSEI number

stale

    Delete stale entries

de-registered

    Delete de-registered entries

### 1.3.4 delete-gbproxy-link <0-65534> (tlli|imsi|sgsn-nsei) IDENT

Command

```
delete-gbproxy-link <0-65534> (tlli|imsi|sgsn-nsei) IDENT
```

Parameters

delete-gbproxy-link

Delete a GBProxy logical link entry by NSEI and identification

<0-65534>

NSEI number

tlli

Delete entries with a matching TLLI (hex)

imsi

Delete entries with a matching IMSI

sgsn-nsei

Delete entries with a matching SGSN NSEI

IDENT

Identification to match

### 1.3.5 delete-gbproxy-peer <0-65534> (only-bvc|only-nsvc|all) [dry-run]

Command

```
delete-gbproxy-peer <0-65534> (only-bvc|only-nsvc|all) [dry-run]
```

Parameters

delete-gbproxy-peer

Delete a GBProxy peer by NSEI and optionally BVCI

<0-65534>

NSEI number

only-bvc

Only delete BSSGP connections (BVC)

only-nsvc

Only delete dynamic NS connections (NS-VC)

all

Delete BVC and dynamic NS connections

[dry-run]

Show what would be deleted instead of actually deleting

### 1.3.6 delete-gbproxy-peer <0-65534> bvcI <2-65534>

Command

```
delete-gbproxy-peer <0-65534> bvcI <2-65534>
```

Parameters

delete-gbproxy-peer

Delete a GBProxy peer by NSEI and optionally BVCI

<0-65534>

NSEI number

bvcI

Only delete peer with a matching BVCI

<2-65534>

BVCI number

### 1.3.7 disable

Command

```
disable
```

Parameters

disable

Turn off privileged mode command

### 1.3.8 logging color (0|1)

Command

```
logging color (0|1)
```

Parameters

logging

Configure logging

color

Configure color-printing for log messages

0

Don't use color for printing messages

1

Use color for printing messages

### 1.3.9 logging disable

Command

```
logging disable
```

Parameters

logging

Configure logging

disable

Disables logging to this vty

### 1.3.10 logging enable

This command is required to make logging commands available on the telnet VTY.

Command

```
logging enable
```

Parameters

logging

Configure logging

enable

Enables logging to this vty

### 1.3.11 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

Command

```
logging filter all (0|1)
```

Parameters

logging

Configure logging

filter

Filter log messages

all

Do you want to log all messages?

0

Only print messages matched by other filters

1

Bypass filter and print all messages

### 1.3.12 logging filter nservc (nsei|nsvci) <0-65535>

Command

```
logging filter nservc (nsei|nsvci) <0-65535>
```

Parameters

logging

Configure logging

filter

Filter log messages

nservc

Filter based on NS Virtual Connection

nsei

Identify NS-VC by NSEI

nsvci

Identify NS-VC by NSVCI

<0-65535>

Numeric identifier

### 1.3.13 logging level (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|l...

Command

```
logging level (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats| ↵
    lgsup|loap|lss7|lscap|lsua|lm3ua|lmgcp|ljibuf|lrspro) (debug|info|notice|error| ↵
    fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

gprs

GPRS Packet Service

ns

GPRS Network Service (NS)

bssgp

GPRS BSS Gateway Protocol (BSSGP)

lglobal

Library-internal global log family

llapd  
LAPD in libosmogsm

linp  
A-bis Input Subsystem

lmux  
A-bis B-Subchannel TRAU Frame Multiplex

lmi  
A-bis Input Driver for Signalling

lmib  
A-bis Input Driver for B-Channels (voice)

lsms  
Layer3 Short Message Service (SMS)

lctrl  
Control Interface

lgtp  
GPRS GTP library

lstats  
Statistics messages and logging

lgsup  
Generic Subscriber Update Protocol

loap  
Osmocom Authentication Protocol

lss7  
libosmo-sigtran Signalling System 7

lsccp  
libosmo-sigtran SCCP Implementation

lsua  
libosmo-sigtran SCCP User Adaptation

lm3ua  
libosmo-sigtran MTP3 User Adaptation

lmgcp  
libosmo-mgcp Media Gateway Control Protocol

ljbuf  
libosmo-netif Jitter Buffer

lrspc  
Remote SIM protocol

debug  
Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.3.14 logging level force-all (debug|info|notice|error|fatal)

Command

```
logging level force-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.3.15 logging level set-all (debug|info|notice|error|fatal)

Command

```
logging level set-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

set-all

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.3.16 logging print category (0|1)

Command

```
logging print category (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem name

### 1.3.17 logging print category-hex (0|1)

Command

```
logging print category-hex (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')

### 1.3.18 logging print extended-timestamp (0|1)

Command

```
logging print extended-timestamp (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.3.19 logging print file (0|1|basename) [last]

Command

```
logging print file (0|1|basename) [last]
```

Parameters

logging

Configure logging

print

Log output settings

file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

basename

Prefix each log message with the source file's basename (strip leading paths) and line

[last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.3.20 logging print level (0|1)

Command

```
logging print level (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.3.21 logging set-log-mask MASK

Command

```
logging set-log-mask MASK
```

Parameters

logging

Configure logging

set-log-mask

Set the logmask of this logging target

MASK

List of logging categories to log, e.g. 'abc:mno:xyz'. Available log categories depend on the specific application, refer to the 'logging level' command. Optionally add individual log levels like 'abc,1:mno,3:xyz,5', where the level numbers are LOGL\_DEBUG=1 LOGL\_INFO=3 LOGL\_NOTICE=5 LOGL\_ERROR=7 LOGL\_FATAL=8

### 1.3.22 logging timestamp (0|1)

Command

```
logging timestamp (0|1)
```

Parameters

logging

Configure logging

timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp

### 1.3.23 logp (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgs...

Command

```
logp (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats|lgsup|loap ←  
      |lss7|lscpp|lsua|lm3ua|lmgcp|ljbuf|lrspro) (debug|info|notice|error|fatal) . ←  
LOGMESSAGE
```

Parameters

logp

Print a message on all log outputs; useful for placing markers in test logs

gprs  
    GPRS Packet Service

ns  
    GPRS Network Service (NS)

bssgp  
    GPRS BSS Gateway Protocol (BSSGP)

lglobal  
    Library-internal global log family

llapd  
    LAPD in libosmogsm

linp  
    A-bis Input Subsystem

lmux  
    A-bis B-Subchannel TRAU Frame Multiplex

lmi  
    A-bis Input Driver for Signalling

lmib  
    A-bis Input Driver for B-Channels (voice)

lsms  
    Layer3 Short Message Service (SMS)

lctrl  
    Control Interface

lgtp  
    GPRS GTP library

lstats  
    Statistics messages and logging

lgsup  
    Generic Subscriber Update Protocol

loap  
    Osmocom Authentication Protocol

lss7  
    libosmo-sigtran Signalling System 7

lsccp  
    libosmo-sigtran SCCP Implementation

lsua  
    libosmo-sigtran SCCP User Adaptation

lm3ua  
    libosmo-sigtran MTP3 User Adaptation

lmgcp

libosmo-mgcp Media Gateway Control Protocol

ljbuf

libosmo-netif Jitter Buffer

lspro

Remote SIM protocol

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

.LOGMESSAGE

Arbitrary message to log on given category and log level

### 1.3.24 no logging level force-all

Command

```
no logging level force-all
```

Parameters

no

Negate a command or set its defaults

logging

Configure logging

level

Set the log level for a specified category

force-all

Release any globally forced log level set with 'logging level force-all <level>'

### 1.3.25 nsvc (nsei|nsvci) <0-65535> (block|unblock|reset)

Command

```
nsvc (nsei|nsvci) <0-65535> (block|unblock|reset)
```

Parameters

nsvc

Perform an operation on a NSVC

nsei

NSEI to identify NS-VC Identifier (NS-VCI)

nsvci

NS-VC Identifier (NS-VCI)

<0-65535>

The NSEI

block

Initiate BLOCK procedure

unblock

Initiate UNBLOCK procedure

reset

Initiate RESET procedure

### 1.3.26 show alarms

Command

```
show alarms
```

Parameters

show

Show running system information

alarms

Show current logging configuration

### 1.3.27 show asciidoc counters

Command

```
show asciidoc counters
```

Parameters

show

    Show running system information

asciidoc

    Asciidoc generation

counters

    Generate table of all registered counters

### 1.3.28 show gbproxy [stats]

Command

```
show gbproxy [stats]
```

Parameters

show

    Show running system information

gbproxy

    Display information about the Gb proxy

[stats]

    Show statistics

### 1.3.29 show gbproxy links

Command

```
show gbproxy links
```

Parameters

show

    Show running system information

gbproxy

    Display information about the Gb proxy

links

    Show logical links

### 1.3.30 show history

Command

```
show history
```

Parameters

show

    Show running system information

history

    Display the session command history

### 1.3.31 show logging vty

Command

```
show logging vty
```

Parameters

show

    Show running system information

logging

    Show current logging configuration

vty

    Show current logging configuration for this vty

### 1.3.32 show ns

Command

```
show ns
```

Parameters

show

    Show running system information

ns

    Display information about the NS protocol

### 1.3.33 show ns (nsei|nsvc) <0-65535> [stats]

Command

```
show ns (nsei|nsvc) <0-65535> [stats]
```

Parameters

show

    Show running system information

ns

    Display information about the NS protocol

nsei

    Select one NSE by its NSE Identifier

nsvc

    Select one NSE by its NS-VC Identifier

<0-65535>

    The Identifier of selected type

[stats]

    Include Statistics

### 1.3.34 show ns persistent

Command

```
show ns persistent
```

Parameters

show

    Show running system information

ns

    Display information about the NS protocol

persistent

    Show only persistent NS

### 1.3.35 show ns stats

Command

```
show ns stats
```

Parameters

show

    Show running system information

ns

    Display information about the NS protocol

stats

    Include statistics

### 1.3.36 show online-help

Command

```
show online-help
```

Parameters

show

    Show running system information

online-help

    Online help

### 1.3.37 show rate-counters

Command

```
show rate-counters
```

Parameters

show

    Show running system information

rate-counters

    Show all rate counters

### 1.3.38 show startup-config

Command

```
show startup-config
```

Parameters

show

    Show running system information

startup-config

    Contentes of startup configuration

### 1.3.39 show stats

Command

```
show stats
```

Parameters

show

    Show running system information

stats

    Show statistical values

### 1.3.40 show stats level (global|peer|subscriber)

Command

```
show stats level (global|peer|subscriber)
```

Parameters

show

    Show running system information

stats

    Show statistical values

level

    Set the maximum group level

global

    Show global groups only

peer

    Show global and network peer related groups

subscriber

    Show global, peer, and subscriber groups

### 1.3.41 show talloc-context (application|all) (full|brief|DEPTH)

Command

```
show talloc-context (application|all) (full|brief|DEPTH)
```

Parameters

show

    Show running system information

talloc-context

    Show talloc memory hierarchy

application

    Application's context

all

    All contexts, if NULL-context tracking is enabled

full

    Display a full talloc memory hierarchy

brief

    Display a brief talloc memory hierarchy

DEPTH

    Specify required maximal depth value

### 1.3.42 show talloc-context (application|all) (full|brief|DEPTH) filter REGEXP

Command

```
show talloc-context (application|all) (full|brief|DEPTH) filter REGEXP
```

Parameters

show

    Show running system information

talloc-context

    Show talloc memory hierarchy

application

    Application's context

all

    All contexts, if NULL-context tracking is enabled

full

    Display a full talloc memory hierarchy

brief

    Display a brief talloc memory hierarchy

DEPTH

    Specify required maximal depth value

filter

    Filter chunks using regular expression

REGEXP

    Regular expression

### 1.3.43 show talloc-context (application|all) (full|brief|DEPTH) tree ADDRESS

Command

```
show talloc-context (application|all) (full|brief|DEPTH) tree ADDRESS
```

Parameters

show

    Show running system information

talloc-context

    Show talloc memory hierarchy

application

    Application's context

all

    All contexts, if NULL-context tracking is enabled

full

Display a full talloc memory hierarchy

brief

Display a brief talloc memory hierarchy

DEPTH

Specify required maximal depth value

tree

Display only a specific memory chunk

ADDRESS

Chunk address (e.g. 0xdeadbeef)

#### 1.3.44 show version

Command

```
show version
```

Parameters

show

Show running system information

version

Displays program version

#### 1.3.45 terminal length <0-512>

Command

```
terminal length <0-512>
```

Parameters

terminal

Set terminal line parameters

length

Set number of lines on a screen

<0-512>

Number of lines on screen (0 for no pausing)

### 1.3.46 terminal monitor

Command

```
terminal monitor
```

Parameters

terminal

    Set terminal line parameters

monitor

    Copy debug output to the current terminal line

### 1.3.47 terminal no length

Command

```
terminal no length
```

Parameters

terminal

    Set terminal line parameters

no

    Negate a command or set its defaults

length

    Set number of lines on a screen

### 1.3.48 terminal no monitor

Command

```
terminal no monitor
```

Parameters

terminal

    Set terminal line parameters

no

    Negate a command or set its defaults

monitor

    Copy debug output to the current terminal line

### 1.3.49 who

Command

```
who
```

Parameters

who

Display who is on vty

## 1.4 config

The config node is the root for all configuration commands, which are identical to the config file format. Changes made on the telnet VTY can be made persistent with the 'write file' command.

### 1.4.1 banner motd default

Command

```
banner motd default
```

Parameters

banner

Set banner string

motd

Strings for motd

default

Default string

### 1.4.2 banner motd file [FILE]

Command

```
banner motd file [FILE]
```

Parameters

banner

Set banner

motd

Banner for motd

file

Banner from a file

[FILE]

Filename

### 1.4.3 enable password (8|) WORD

Command

```
enable password (8 | ) WORD
```

Parameters

enable

Modify enable password parameters

password

Assign the privileged level password

8

Specifies a HIDDEN password will follow

dummy string

WORD

The HIDDEN 'enable' password string

### 1.4.4 enable password LINE

Command

```
enable password LINE
```

Parameters

enable

Modify enable password parameters

password

Assign the privileged level password

LINE

The UNENCRYPTED (cleartext) 'enable' password

### 1.4.5 gbproxy

Command

```
gbproxy
```

Parameters

gbproxy

Configure the Gb proxy

### 1.4.6 hostname WORD

Command

```
hostname WORD
```

Parameters

hostname

Set system's network name

WORD

This system's network name

### 1.4.7 line vty

Command

```
line vty
```

Parameters

line

Configure a terminal line

vty

Virtual terminal

### 1.4.8 log alarms <2-32700>

Command

```
log alarms <2-32700>
```

Parameters

log

Configure logging sub-system

alarms

Logging alarms to osmo\_strb

<2-32700>

Maximum number of messages to log

### 1.4.9 log file .FILENAME

Command

```
log file .FILENAME
```

Parameters

log

Configure logging sub-system

file

Logging to text file

.FILENAME

Filename

### 1.4.10 log gsmtap [HOSTNAME]

Command

```
log gsmtap [HOSTNAME]
```

Parameters

log

Configure logging sub-system

gsmtap

Logging via GSMTAP

[HOSTNAME]

Host name to send the GSMTAP logging to (UDP port 4729)

### 1.4.11 log stderr

Command

```
log stderr
```

Parameters

log

Configure logging sub-system

stderr

Logging via STDERR of the process

### 1.4.12 log syslog (authpriv|cron|daemon|ftp|lpr|mail|news|user|uucp)

Command

```
log syslog (authpriv|cron|daemon|ftp|lpr|mail|news|user|uucp)
```

Parameters

log

Configure logging sub-system

syslog

Logging via syslog

authpriv

Security/authorization messages facility

cron

Clock daemon (cron/at) facility

daemon

General system daemon facility

ftp

Ftp daemon facility

lpr

Line printer facility

mail

Mail facility

news

News facility

user

Generic facility

uucp

UUCP facility

### 1.4.13 log syslog local <0-7>

Command

```
log syslog local <0-7>
```

Parameters

log

Configure logging sub-system

syslog

Logging via syslog

local

Syslog LOCAL facility

<0-7>

Local facility number

#### 1.4.14 no banner motd

Command

```
no banner motd
```

Parameters

no

Negate a command or set its defaults

banner

Set banner string

motd

Strings for motd

#### 1.4.15 no enable password

Command

```
no enable password
```

Parameters

no

Negate a command or set its defaults

enable

Modify enable password parameters

password

Assign the privileged level password

#### 1.4.16 no hostname [HOSTNAME]

Command

```
no hostname [HOSTNAME]
```

Parameters

no

Negate a command or set its defaults

hostname

Reset system's network name

[HOSTNAME]

Host name of this router

### 1.4.17 no log alarms

Command

```
no log alarms
```

Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

alarms

Logging alarms to osmo\_strb

### 1.4.18 no log file .FILENAME

Command

```
no log file .FILENAME
```

Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

file

Logging to text file

.FILENAME

Filename

### 1.4.19 no log stderr

Command

```
no log stderr
```

Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

stderr

Logging via STDERR of the process

### 1.4.20 no log syslog

Command

```
no log syslog
```

Parameters

no

Negate a command or set its defaults

log

Configure logging sub-system

syslog

Logging via syslog

### 1.4.21 no service advanced-vty

Command

```
no service advanced-vty
```

Parameters

no

Negate a command or set its defaults

service

Set up miscellaneous service

advanced-vty

Enable advanced mode vty interface

### 1.4.22 no service terminal-length [<0-512>]

Command

```
no service terminal-length [<0-512>]
```

Parameters

no

Negate a command or set its defaults

service

Set up miscellaneous service

terminal-length

System wide terminal length configuration

[<0-512>]

Number of lines of VTY (0 means no line control)

### 1.4.23 no stats reporter log

Command

```
no stats reporter log
```

Parameters

no

Negate a command or set its defaults

stats

Configure stats sub-system

reporter

Configure a stats reporter

log

Report to the logger

### 1.4.24 no stats reporter statsd

Command

```
no stats reporter statsd
```

Parameters

no

Negate a command or set its defaults

stats

Configure stats sub-system

reporter

Configure a stats reporter

statsd

Report to a STATSD server

### 1.4.25 ns

Command

```
ns
```

Parameters

ns

Configure the GPRS Network Service

### 1.4.26 password (8|) WORD

Command

```
password (8 | ) WORD
```

Parameters

password

Assign the terminal connection password

8

Specifies a HIDDEN password will follow

dummy string

WORD

The HIDDEN line password string

### 1.4.27 password LINE

Command

```
password LINE
```

Parameters

password

Assign the terminal connection password

LINE

The UNENCRYPTED (cleartext) line password

### 1.4.28 service advanced-vty

Command

```
service advanced-vty
```

Parameters

service

Set up miscellaneous service

advanced-vty

Enable advanced mode vty interface

### 1.4.29 service terminal-length <0-512>

Command

```
service terminal-length <0-512>
```

Parameters

service

Set up miscellaneous service

terminal-length

System wide terminal length configuration

<0-512>

Number of lines of VTY (0 means no line control)

### 1.4.30 show history

Command

```
show history
```

Parameters

show

Show running system information

history

Display the session command history

### 1.4.31 stats interval <1-65535>

Command

```
stats interval <1-65535>
```

Parameters

stats

Configure stats sub-system

interval

Set the reporting interval

<1-65535>

Interval in seconds

### 1.4.32 stats reporter log

Command

```
stats reporter log
```

Parameters

stats

Configure stats sub-system

reporter

Configure a stats reporter

log

Report to the logger

### 1.4.33 stats reporter statsd

Command

```
stats reporter statsd
```

Parameters

stats

Configure stats sub-system

reporter

Configure a stats reporter

statsd

Report to a STATSD server

## 1.5 config-log

The log node is commonly available in all Osmocom programs and allows configuring logging to stderr and/or log files, including logging category and level filtering as well as output formatting options. Note that the 'logging enable' command is required to make logging commands available on the telnet VTY.

### 1.5.1 logging color (0|1)

Command

```
logging color (0|1)
```

Parameters

logging

Configure logging

color

Configure color-printing for log messages

0

Don't use color for printing messages

1

Use color for printing messages

### 1.5.2 logging filter all (0|1)

Disable/enable general log output on a given target. Typically, 'logging filter all 1' allows to see the usual log output on a given target. Setting to '0' can be useful when logging to the telnet VTY console: mute all log output to allow typing VTY commands on the telnet prompt without interference from log output; 'logging filter all 1' then re-enables logging in the same log output configuration as before. Some applications provide more specific filters, e.g. to log a given IMSI only. To employ such filters, set 'logging filter all 0' to disable general logging, and then enable a more specific filter instead.

Command

```
logging filter all (0|1)
```

Parameters

logging

Configure logging

filter

Filter log messages

all

Do you want to log all messages?

0

Only print messages matched by other filters

1

Bypass filter and print all messages

### 1.5.3 logging filter nservc (nsei|nsvci) <0-65535>

Command

```
logging filter nservc (nsei|nsvci) <0-65535>
```

Parameters

logging

Configure logging

filter

Filter log messages

nsvc

Filter based on NS Virtual Connection

nsei

Identify NS-VC by NSEI

nsvci

Identify NS-VC by NSVCI

<0-65535>

Numeric identifier

#### 1.5.4 logging level (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|l...

Command

```
logging level (|gprs|ns|bssgp|lglobal|llapd|linp|lmux|lmi|lmib|lsms|lctrl|lgtp|lstats| ↵
    lgsup|loap|lss7|lscap|lsua|lm3ua|lmgcp|ljibuf|lrspro) (debug|info|notice|error| ↵
    fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

gprs

GPRS Packet Service

ns

GPRS Network Service (NS)

bssgp

GPRS BSS Gateway Protocol (BSSGP)

lglobal

Library-internal global log family

llapd

LAPD in libosmogsm

linp

A-bis Input Subsystem

lmux

A-bis B-Subchannel TRAU Frame Multiplex

lmi

A-bis Input Driver for Signalling

lmib

A-bis Input Driver for B-Channels (voice)

lsms

Layer3 Short Message Service (SMS)

lctrl

Control Interface

lgtp

GPRS GTP library

lstats

Statistics messages and logging

lgsup

Generic Subscriber Update Protocol

loap

Osmocom Authentication Protocol

lss7

libosmo-sigtran Signalling System 7

lscpp

libosmo-sigtran SCCP Implementation

lsua

libosmo-sigtran SCCP User Adaptation

lm3ua

libosmo-sigtran MTP3 User Adaptation

lmgcp

libosmo-mgcp Media Gateway Control Protocol

ljbuf

libosmo-netif Jitter Buffer

lspro

Remote SIM protocol

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.5.5 logging level force-all (debug|info|notice|error|fatal)

Command

```
logging level force-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

force-all

Globally force all logging categories to a specific level. This is released by the 'no logging level force-all' command. Note: any 'logging level <category> <level>' commands will have no visible effect after this, until the forced level is released.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.5.6 logging level set-all (debug|info|notice|error|fatal)

Command

```
logging level set-all (debug|info|notice|error|fatal)
```

Parameters

logging

Configure logging

level

Set the log level for a specified category

set-all

Once-off set all categories to the given log level. There is no single command to take back these changes -- each category is set to the given level, period.

debug

Log debug messages and higher levels

info

Log informational messages and higher levels

notice

Log noticeable messages and higher levels

error

Log error messages and higher levels

fatal

Log only fatal messages

### 1.5.7 logging print category (0|1)

Command

```
logging print category (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem name

### 1.5.8 logging print category-hex (0|1)

Command

```
logging print category-hex (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

category-hex

Configure log message

0

Don't prefix each log message

1

Prefix each log message with category/subsystem nr in hex ('<000b>')

### 1.5.9 logging print extended-timestamp (0|1)

Command

```
logging print extended-timestamp (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

extended-timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp with YYYYMMDDhhmmssnnn

### 1.5.10 logging print file (0|1|basename) [last]

Command

```
logging print file (0|1|basename) [last]
```

Parameters

logging

Configure logging

print

Log output settings

file

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the source file and line

basename

Prefix each log message with the source file's basename (strip leading paths) and line

[last]

Log source file info at the end of a log line. If omitted, log source file info just before the log text.

### 1.5.11 logging print level (0|1)

Command

```
logging print level (0|1)
```

Parameters

logging

Configure logging

print

Log output settings

level

Configure log message

0

Don't prefix each log message

1

Prefix each log message with the log level name

### 1.5.12 logging timestamp (0|1)

Command

```
logging timestamp (0|1)
```

Parameters

logging

Configure logging

timestamp

Configure log message timestamping

0

Don't prefix each log message

1

Prefix each log message with current timestamp

### 1.5.13 no logging level force-all

Command

```
no logging level force-all
```

Parameters

no

Negate a command or set its defaults

logging

Configure logging

level

Set the log level for a specified category

force-all

Release any globally forced log level set with 'logging level force-all <level>'

## 1.6 config-stats

### 1.6.1 disable

Command

```
disable
```

Parameters

disable

Disable the reporter

### 1.6.2 enable

Command

```
enable
```

Parameters

enable

Enable the reporter

### 1.6.3 level (global|peer|subscriber)

Command

```
level (global|peer|subscriber)
```

Parameters

level

Set the maximum group level

global

Report global groups only

peer

Report global and network peer related groups

subscriber

Report global, peer, and subscriber groups

#### 1.6.4 local-ip ADDR

Command

```
local-ip ADDR
```

Parameters

local-ip

Set the IP address to which we bind locally

ADDR

IP Address

#### 1.6.5 mtu <100-65535>

Command

```
mtu <100-65535>
```

Parameters

mtu

Set the maximum packet size

<100-65535>

Size in byte

#### 1.6.6 no local-ip

Command

```
no local-ip
```

Parameters

no

Negate a command or set its defaults

local-ip

Set the IP address to which we bind locally

#### 1.6.7 no mtu

Command

```
no mtu
```

Parameters

no

Negate a command or set its defaults

mtu

Set the maximum packet size

### 1.6.8 no prefix

Command

```
no prefix
```

Parameters

no

Negate a command or set its defaults

prefix

Set the item name prefix

### 1.6.9 prefix PREFIX

Command

```
prefix PREFIX
```

Parameters

prefix

Set the item name prefix

PREFIX

The prefix string

### 1.6.10 remote-ip ADDR

Command

```
remote-ip ADDR
```

Parameters

remote-ip

Set the remote IP address to which we connect

ADDR

IP Address

### 1.6.11 remote-port <1-65535>

Command

```
remote-port <1-65535>
```

Parameters

remote-port

Set the remote port to which we connect

<1-65535>

Remote port number

## 1.7 config-line

### 1.7.1 bind A.B.C.D [<0-65535>]

Command

```
bind A.B.C.D [<0-65535>]
```

Parameters

bind

Accept VTY telnet connections on local interface

A.B.C.D

Local interface IP address (default: 127.0.0.1)

[<0-65535>]

Local TCP port number

### 1.7.2 login

Command

```
login
```

Parameters

login

Enable password checking

### 1.7.3 no login

Command

```
no login
```

Parameters

no

Negate a command or set its defaults

login

Enable password checking

## 1.8 config-ns

### 1.8.1 encapsulation framerelay-gre enabled (1|0)

Command

```
encapsulation framerelay-gre enabled (1|0)
```

Parameters

encapsulation

    NS encapsulation options

framerelay-gre

    NS over Frame Relay over GRE Encapsulation

enabled

    Enable or disable Frame Relay over GRE

1

    Enable

0

    Disable

### 1.8.2 encapsulation framerelay-gre local-ip A.B.C.D

Command

```
encapsulation framerelay-gre local-ip A.B.C.D
```

Parameters

encapsulation

    NS encapsulation options

framerelay-gre

    NS over Frame Relay over GRE Encapsulation

local-ip

    Set the IP address on which we listen for NS/FR/GRE

A.B.C.D

    IP Address

### 1.8.3 encapsulation udp dscp <0-255>

Command

```
encapsulation udp dscp <0-255>
```

Parameters

encapsulation

    NS encapsulation options

udp

    NS over UDP Encapsulation

dscp

    Set DSCP/TOS on the UDP socket

<0-255>

    DSCP Value

### 1.8.4 encapsulation udp local-ip A.B.C.D

Command

```
encapsulation udp local-ip A.B.C.D
```

Parameters

encapsulation

    NS encapsulation options

udp

    NS over UDP Encapsulation

local-ip

    Set the IP address on which we listen for NS/UDP

A.B.C.D

    IP Address

### 1.8.5 encapsulation udp local-port <0-65535>

Command

```
encapsulation udp local-port <0-65535>
```

Parameters

encapsulation

    NS encapsulation options

udp

NS over UDP Encapsulation

local-port

Set the UDP port on which we listen for NS/UDP

<0-65535>

UDP port number

### 1.8.6 no nse <0-65535>

Command

```
no nse <0-65535>
```

Parameters

no

Delete Persistent NS Entity

nse

Delete Persistent NS Entity

<0-65535>

NS Entity ID (NSEI)

### 1.8.7 nse <0-65535> encapsulation (udp|framerelay-gre)

Command

```
nse <0-65535> encapsulation (udp|framerelay-gre)
```

Parameters

nse

Persistent NS Entity

<0-65535>

NS Entity ID (NSEI)

encapsulation

Encapsulation for NS

udp

UDP/IP Encapsulation

framerelay-gre

Frame-Relay/GRE/IP Encapsulation

### 1.8.8 nse <0-65535> fr-dlci <16-1007>

Command

```
nse <0-65535> fr-dlci <16-1007>
```

Parameters

nse

Persistent NS Entity

<0-65535>

NS Entity ID (NSEI)

fr-dlci

Frame Relay DLCI

<16-1007>

Frame Relay DLCI Number

### 1.8.9 nse <0-65535> nsvci <0-65534>

Command

```
nse <0-65535> nsvci <0-65534>
```

Parameters

nse

Persistent NS Entity

<0-65535>

NS Entity ID (NSEI)

nsvci

NS Virtual Connection

<0-65534>

NS Virtual Connection ID (NSVCI)

### 1.8.10 nse <0-65535> remote-ip A.B.C.D

Command

```
nse <0-65535> remote-ip A.B.C.D
```

Parameters

nse

Persistent NS Entity

```
<0-65535>
    NS Entity ID (NSEI)

remote-ip
    Remote IP Address

A.B.C.D
    Remote IP Address
```

### 1.8.11 nse <0-65535> remote-port <0-65535>

Command

```
nse <0-65535> remote-port <0-65535>
```

Parameters

```
nse
    Persistent NS Entity

<0-65535>
    NS Entity ID (NSEI)

remote-port
    Remote UDP Port

<0-65535>
    Remote UDP Port Number
```

### 1.8.12 nse <0-65535> remote-role (sgsn|bss)

Command

```
nse <0-65535> remote-role (sgsn|bss)
```

Parameters

```
nse
    Persistent NS Entity

<0-65535>
    NS Entity ID (NSEI)

remote-role
    Remote NSE Role

sgsn
    Remote Peer is SGSN

bss
    Remote Peer is BSS
```

### 1.8.13 timer (tns-block|tns-block-retries|tns-reset|tns-reset-retries|tns-test|tns-aliv...

Command

```
timer (tns-block|tns-block-retries|tns-reset|tns-reset-retries|tns-test|tns-alive|tns- ↵
      alive-retries|tsns-prov) <0-65535>
```

Parameters

timer

Network Service Timer

tns-block

(un)blocking Timer (Tns-block) timeout

tns-block-retries

(un)blocking Timer (Tns-block) number of retries

tns-reset

Reset Timer (Tns-reset) timeout

tns-reset-retries

Reset Timer (Tns-reset) number of retries

tns-test

Test Timer (Tns-test) timeout

tns-alive

Alive Timer (Tns-alive) timeout

tns-alive-retries

Alive Timer (Tns-alive) number of retries

tsns-prov

SNS Provision Timer (Tsns-prov) timeout

<0-65535>

Timer Value

## 1.9 config-gbproxy

Configure the Gb proxy

### 1.9.1 acquire-imsi

Command

```
acquire-imsi
```

Parameters

acquire-imsi

Acquire the IMSI before establishing a LLC connection (Experimental)

### 1.9.2 core-access-point-name (APN|none)

Command

```
core-access-point-name (APN|none)
```

Parameters

core-access-point-name

    Use this access point name (APN) for the backbone

APN

    Replace APN by this string

none

    Remove APN

### 1.9.3 core-mobile-country-code <1-999>

Command

```
core-mobile-country-code <1-999>
```

Parameters

core-mobile-country-code

    Use this country code for the core network

<1-999>

    MCC value

### 1.9.4 core-mobile-network-code <1-999>

Command

```
core-mobile-network-code <1-999>
```

Parameters

core-mobile-network-code

    Use this network code for the core network

<1-999>

    NCC value

### 1.9.5 link stored-msgs-max-length <1-99999>

Command

```
link stored-msgs-max-length <1-99999>
```

Parameters

link

    Set TLLI parameters

stored-msgs-max-length

    Limit list length

<1-99999>

    Maximum number of msgb stored in the logical link waiting to acquire its IMSI

### 1.9.6 link-list clean-stale-timer <1-999999>

Command

```
link-list clean-stale-timer <1-999999>
```

Parameters

link-list

    Set TLLI list parameters

clean-stale-timer

    Periodic timer to clean stale links

<1-999999>

    Frequency at which the periodic timer is fired (in seconds)

### 1.9.7 link-list keep-mode (never|re-attach|identified|always)

Command

```
link-list keep-mode (never|re-attach|identified|always)
```

Parameters

link-list

    Set TLLI list parameters

keep-mode

    How to keep entries for detached logical links

never

    Discard entry immediately after detachment

re-attach

Keep entry if a re-attachment has been requested

identified

Keep entry if it is associated with an IMSI

always

Don't discard entries after detachment

### 1.9.8 link-list max-age <1-999999>

Command

```
link-list max-age <1-999999>
```

Parameters

link-list

Set TLLI list parameters

max-age

Limit maximum age

<1-999999>

Maximum age in seconds

### 1.9.9 link-list max-length <1-99999>

Command

```
link-list max-length <1-99999>
```

Parameters

link-list

Set TLLI list parameters

max-length

Limit list length

<1-99999>

Maximum number of logical links in the list

### 1.9.10 match-imsi (patching|routing) .REGEXP

Command

```
match-imsi (patching|routing) .REGEXP
```

Parameters

match-imsi

    Restrict actions to certain IMSIs

patching

    Patch MS related information elements on match only

routing

    Route to the secondary SGSN on match only

.REGEXP

    Regular expression for the IMSI match

### 1.9.11 no acquire-imsi

Command

```
no acquire-imsi
```

Parameters

no

    Negate a command or set its defaults

acquire-imsi

    Acquire the IMSI before establishing a LLC connection (Experimental)

### 1.9.12 no core-access-point-name

Command

```
no core-access-point-name
```

Parameters

no

    Negate a command or set its defaults

core-access-point-name

    Use this access point name (APN) for the backbone

### 1.9.13 no core-mobile-country-code

Command

```
no core-mobile-country-code
```

Parameters

no

Negate a command or set its defaults

core-mobile-country-code

Use this country code for the core network

### 1.9.14 no core-mobile-network-code

Command

```
no core-mobile-network-code
```

Parameters

no

Negate a command or set its defaults

core-mobile-network-code

Use this network code for the core network

### 1.9.15 no link stored-msgs-max-length

Command

```
no link stored-msgs-max-length
```

Parameters

no

Negate a command or set its defaults

link

Set TLLI parameters

stored-msgs-max-length

Limit list length

### 1.9.16 no link-list clean-stale-timer

Command

```
no link-list clean-stale-timer
```

Parameters

no

Negate a command or set its defaults

link-list

Set TLLI list parameters

clean-stale-timer

Periodic timer to clean stale links

### 1.9.17 no link-list max-age

Command

```
no link-list max-age
```

Parameters

no

Negate a command or set its defaults

link-list

Set TLLI list parameters

max-age

Limit maximum age

### 1.9.18 no link-list max-length

Command

```
no link-list max-length
```

Parameters

no

Negate a command or set its defaults

link-list

Set TLLI list parameters

max-length

Limit list length

### 1.9.19 no match-imsi

Command

```
no match-imsi
```

Parameters

no

Negate a command or set its defaults

match-imsi

Restrict actions to certain IMSIs

### 1.9.20 no patch-ptmsi

Command

```
no patch-ptmsi
```

Parameters

no

Negate a command or set its defaults

patch-ptmsi

Patch P-TMSI/TLLI

### 1.9.21 no secondary-sgsn

Command

```
no secondary-sgsn
```

Parameters

no

Negate a command or set its defaults

secondary-sgsn

Route matching LLC connections to a second SGSN (Experimental)

### 1.9.22 patch-ptmsi

Command

```
patch-ptmsi
```

Parameters

patch-ptmsi

Patch P-TMSI/TLLI

### 1.9.23 secondary-sgsn nsei <0-65534>

Command

```
secondary-sgsn nsei <0-65534>
```

Parameters

secondary-sgsn

Route matching LLC connections to a second SGSN (Experimental)

nsei

NSEI to be used in the connection with the SGSN

<0-65534>

The NSEI

### 1.9.24 sgsn nsei <0-65534>

Command

```
sgsn nsei <0-65534>
```

Parameters

sgsn

SGSN information

nsei

NSEI to be used in the connection with the SGSN

<0-65534>

The NSEI